- **8X Sony Blu-ray retail drive with S-ATA interface**
- **enable to read and record all Blu-ray, DVD and CD formats for Windows Vista® and XP with one drive**
- **comes with Blu-ray, DVD and CD software suite from Cyberlink**
- **the box includes:**
  - ✓ Drive BWU-300S
  - ✓ Screws (×4)
  - ✓ Quick Start Guide
  - ✓ Product Information
  - ✓ Software Disc
  - ✓ Serial ATA Cable
  - ✓ Serial ATA Power Adapter

- **8X fast BD recording for BD-R**
- **2X fast BD recording for BD-RE up to 50GB**
- **Stores up to 4 hours 1080 HD video per disc**
- **DVD and CD media compatibility:**

  Read DVD: 16x max.   CD: 48x max

  Write DVD±R: 16x max.   CD-R: 48x max.

  DVD+/-RW:8/6x max.   CD-RW:24x max.

  DVD-RAM: 5x max.

- **S-ATA interface (max. 150 MByte/sec)**
- **12cm and 8cm BD, DVD and CD media supported**
- **Dust protected enclosure**
- **Emergency Eject**

Specifications		8X BD Writer (BWU-300S)		
		Blu-ray disc	**DVD**	**CD**
Transfer Rate read		8x P-CAV (35200 kByte/s)	16x CAV (max. 21600 kByte/s)	48x CAV (max. 7200 kByte/s)
Transfer Rate write	-R	8x P-CAV (35200 kByte/s)	16x CAV (max. 21600 kByte/s)	48x CAV (max. 7200 kByte/s)
	-R DL	8x P-CAV (35200 kByte/s)	8x P-CAV (max. 10800 kByte/s)	./.
	-RE/W	2x CLV (8800 kByte/s)	6x CLV (max. 8200 kByte/s)	24x Z-CLV (max. 3600 kByte/s)
	-RE DL	2x CLV (8800 kByte/s)	./.	./.
	-RAM	./.	5x CLV (max. 6900 kByte/s)	./.
	+R	./.	16x CAV (max. 21600 kByte/s)	./.
	+R9	./.	8x P-CAV (max. 10800 kByte/s)	./.
	+RW	./.	8x Z-CLV (max. 10800 kByte/s)	./.
Access Time		210 ms	170 ms	150 ms
Mechanism		motorized Tray load mechanism for horizontal and vertical use		
Interface		S-ATA		
Burst Tranfer Rate		150 MByte/s		
Cache Memory		8 MByte		
Media/Modes supported		BD-ROM, BD-AV, BD-R(DL), BD-RE(DL), DVD-ROM, DVD-R/-R DL/-RW, DVD +R/+R9/+RW, DVD-RAM; DVD-Video; CD-DA, CD-ROM (XA), CD Extra, Video CD, Photo CD, CD Text		
Weight		0.9 kg		
Dimensions		148mm x 42mm x 198mm		